

# Transformadores Monofásicos

## TIPP

### Dimensionais Mecânicas

Modelo	Potência [VA]	Nº lâmpadas	A [máx] (mm)	B [±2] (mm)	C [máx] (mm)	D [±1] (mm)	E [máx] (mm)	F [±1] (mm)	Massa (kg)	
TR1	50	1	70	52	51 ± 2	89	82	M4	1,5	
TR2	100	2			67 ± 2	105				
TR3	160	3	67 ± 5	117						
TR4	200	4	84	61	78 ± 5	128	3,3			
TR5	250	5			82 ± 5	132	3,5			
TR6	360	6	100	75	73 ± 5	116	120		M5	3,8
TR7	400	7			95 ± 5	138				5,7

